# **Botron B8203 Technical Data Sheet**



#### Overview:

Botron's B8203 High Quality Lightweight Portable Wrist Strap tester has a large 3/4" touch button for easy testing and easy to read LEDs that show low, high and pass. Audible alarm will sound when passing. Works on all standard wrist straps and coil cords. Test ranges from 725k-10megohms.

Product Notes and Features

- Lightweight
- Portable
- · Good for field kits
- LED Light Indicators

#### **PROPERTIES SPECIFICATIONS**

3 lights LED: LED light Low Battery: 9 volts Battery: Weight: 5.1 oz.

3.5" x 4.5" x 1.5" Size: >725k - 10megohm Test Range: +/- 10% Hi 20% Low Accuracy Range:

# LOW PASS HIGH LOW BATT WRIST STRAP TESTER B BOTRON

### PART NUMBERS

**B8203** Portable Wrist Strap Tester

## **OPERATION**

Unscrew two screws on back of unit and insert 9v battery into compartment.

To test wrist straps, plug in banana jack from coil cord into banana jack input on front and press test button.

To test coil cords, unplug coil cord from strap, plug in banana jack. Holding snap end in hand, touch metal coil to the test button and press down.